



KRAMER

CC-BNC/RCA/F

BNC, RCA & F Compression Connectors



Kramer's solder-free compression connectors reduce service calls by supplying strong, secure and lasting connections. Crafted to withstand 80lb (36.3kg) of force, our compression connectors provide full 360° electrical continuity even under the most punishing conditions. The radial design reduces the possibility of an impedance problem and defeats ingress/egress at the connector. Internal "O" sealing rings prevent moisture migration, while the large ferrule surface insures proper RF and digital interfaces

FEATURES

One Compression Tool for All Connectors

Color-Coded Connectors - See table below

25 Connectors Per Package - all models, except for CC-BNC-179 (50 Connectors Per Package), see CONFIGURATIONS



KRAMER

TECHNICAL SPECIFICATIONS

CC-BNC-6, CC-RCA-6, CC-F6,
CC-BNC-R6,
CC-RCA-R6:

Center Conductor: 0.0399" – 0.0418"/1.0135mm – 1.0617mm.
Dielectric: 0.180" – 0.193"/4.572mm – 4.9022mm.
Outer Jacket: 0.265" – 0.305"/6.731mm – 7.747mm

CC-BNC-22,
CC-RCA-22:

Center Conductor: 0.015" – 0.025"/0.381mm – 0.635mm.
Dielectric: 0.095" – 0.105"/2.413mm – 2.667mm.
Outer Jacket: 0.145" – 0.160"/3.683mm – 4.064mm

CC-BNC-59,
CC-RCA-59,
CC-F59,
CC-BNC-R59,
CC-RCA-R59:

Center Conductor: 0.0317" – 0.0339"/0.8052mm – 0.8611mm.
Dielectric: 0.144" – 0.157"/3.6576mm – 3.9878mm.
Outer Jacket: 0.232" – 0.273"/5.8928mm – 6.9342mm

CC-BNC-179,
CC-RCA-179,
CC-RCA-R179:

Center Conductor: 0.015" – 0.025"/0.381mm – 0.635mm.
Dielectric: 0.065" – 0.078"/1.651mm – 1.9812mm.
Outer Jacket: 0.095" – 0.160"/2.413mm – 4.064mm



KRAMER

CONFIGURATIONS

CC-BNC-6	Old Model # - CON-COMP-BNC/M/RG-6; BNC Compression Connector for RG-6 Coax Cable; 25 pieces
CC-BNC-R6	Old Model # - CON-COMP-BNC/M/RA/RG-6; Right Angle BNC Compression Connector for RG-6 Coax Cable; 25 pieces
CC-BNC-22	Old Model # - CON-COMP-BNC/M/22#; BNC Compression Connector for 22 AWG Cable; 25 pieces
CC-BNC-59	Old Model # - CON-COMP-BNC/M/RG-59; BNC Compression Connector for RG-59 Coax Cable; 25 pieces
CC-BNC-R59	Old Model # - CON-COMP-BNC/M/RA/RG-59; Right Angle BNC Compression Connector for RG-59 Coax Cable; 25 pieces
CC-BNC-179	Old Model # - CON-COMP-BNC/M/RG-179(26-28#); BNC Compression Connector for 26-28 AWG Coax Cable; 50 pieces
CC-RCA-6	Old Model # - CON-COMP-RCA/M/RG-6; RCA Compression Connector for RG-6 Coax Cable; 25 pieces
CC-RCA-R6	Old Model # - CON-COMP-RCA/M/RA/RG-6; Right Angle RCA Compression Connector for RG-6 Coax Cable; 25 pieces
CC-RCA-22	Old Model # - CON-COMP-RCA/M/22#; RCA Compression Connector for 22AWG Cable; 25 pieces
CC-RCA-59	Old Model # - CON-COMP-RCA/M/RG-59; RCA Compression Connector for RG-59 Coax Cable; 25 pieces
CC-RCA-R59	Old Model # - CON-COMP-RCA/M/RA/RG-59; Right Angle RCA Compression Connector for RG-59 Coax Cable; 25 pieces
CC-RCA-179	Old Model # - CON-COMP-RCA/M/RG-179(26-28#); RCA Compression Connector for 26-28 AWG Coax Cable; 25 pieces
CC-RCA-R179	Old Model # - CON-COMP-RCA/M/RA/RG-179(26-28#); Right Angle RCA Compression Connector for 26-26 AWG Coax Cable; 25 pieces
CC-F6	Old Model # - CON-COMP-F/M/RG-6; "F" Compression Connector for RG-6 Coax Cable; 25 pieces
CC-F59	Old Model # - CON-COMP-F/M/RG-59; "F" Compression Connector for RG-59 Coax Cable; 25 pieces