



This programmable, handheld remote can directly control all the IR devices in your entertainment system – TV, A/V components, cable, satellite boxes and more. It is ideal for use in home theaters, family rooms, kitchens or bedrooms. The brilliant 2" color LCD screen displays up to 48 devices. When used with a compatible Complete Control base station, like the MRF-350 and MRF-260, the MX-790 controls integrated A/V components through walls and cabinet doors, or even from outside. There is no need to point the remote control at the components or even be in the same room.

- Handheld remote with 2" color LCD screen
- Displays up to six buttons per screen
- Delivers one-way control of IR devices
- Operates on standard AA alkaline batteries
- MX-790i features 433 MHz frequency for international & highly-populated markets

SPECIFICATIONS

SKU	MX-790, MX-790i
UPC	656787-705166 (MX-790), 656787-705173 (MX-790i)
Microprocessor	ARM Cortex
LCD	240 x 320, 2" TFT LCD
IR	SMD TYPE x 2EA
IR Range (Line of Sight via Infrared)	30 to 50 feet, depending on the environment
RF Range (Radio Frequency)	50 to 100 feet, depending on the environment
RF Frequency	418 MHz (MX-790), 433 MHz (MX-790i)
Batteries	Four AA Alkaline Batteries (included)
Operating Temp	32 - 104 F / 0~40 °C
Dimensions	W: 2.04" / 52mm H: 8.86" / 225mm D: 1.08" / 27.5mm
Weight	7.83oz / 222g (with battery loaded)
System	Complete Control® Professional programming required
In The Box	MX-790 Remote Control, 4x AA Alkaline Batteries, USB Type C-Cable
Warranty	Please visit www.urc-automation.com/warranty

